

PC1404 South Africa Addendum

This document identifies programming defaults for South Africa that differ from the standard defaults in the following publication:
PC1404 Installation Guide
 • PN# 29008013 •

Defaults

Section	Pg.	Description	Option	South African Default
[005] Subsect. [01]	17	System Times	Exit Delay	045
[005] Subsect. [09]	17	System Times	Bell Time-out (BTO)	003
[009]	17	Main Board PGM Output Programming	Onboard PGM 1 Type	10
[010]	17	PC5208 PGM Output Programming	PGM 3 and PGM 4	05 30
[013]	18	First System Options	Option 5, Auto-Arm Schedule in [*][6] + Installer Prog./ Auto-Arm Schedule in Installer Prog. Only	OFF
			Option 6, Audible Exit Fault Enabled/Audible Exit Fault Disabled	OFF
[015]	18	Third System Options	Option 2, [P] Key Audible (Bell/Beeps)/[P] Key Silent	ON
			Option 7, TLM Enabled/TLM Disabled	OFF
[016]	18	Fourth System Options	Option 2, Trouble Light Flashes if AC Fails/Trouble Light Does not Flash	ON
[018]	19	Sixth System Options	Option 5, Keypad Buzzer Follows Bell Enabled/Keypad Buzzer Follows Bell Disabled	ON
[168]	21	Daylight Savings Time Begins	Month	004
			Week	001
[169]	21	Daylight Savings Time Ends	Month	010
			Week	005
[328]	22	Miscellaneous Alarm Reporting Codes	Recent Closing	00
			Burglary Not Verified	00
[341]	23	Miscellaneous Closing (Arming) Reporting Codes	Automatic Zone Bypass	FF
			Late to Close	00
[347]	24	Misc. Maintenance Reporting Codes	DLS Lead in and Lead out	FF
			Installer Lead in and Lead out	FF
[350]	24	Communicator Format Options	1st to 4th Telephone Numbers	03
[367]	25	Opening/Closing Comm. Call Directions	Option 1, First Telephone Number	ON
[377]	25	Communication Variables	Swinger Shutdown (Alarm and Rest)	004
			TLM Trouble Delay	040
[380]	25	First Communicator Option	Option 6, Alternate Backup Dialing Enabled/Call Primary Number, Backup to Secondary	ON
[501]	27	PGM 1 Attributes	Options 1, 2, 6-8	ON
[502]	27	PGM 2 Attributes	Option 8	ON
[501]-[514]; [551]-[564]	28	10 System Event (with Event Options)	Option 8, Output Follows PGM Timer	ON
[701]	29	First International Options	Option 1, 50 Hz AC/60 Hz AC	ON
[702]	29	Second International Options	Option 1, Pulse Dialing Make/Break Ratio is 33/67/ Pulse Dialing Make/Break Ratio is 40/60	ON

