


TL280LE-LAT, LE2080-LAT Technical Manual













Introduction

The TL280LE-LAT is an LTE/HSPA/Ethernet communication module. Use it with NEO Power series alarm control panels. The LE2080 is an LTE/HSPA communications module. These products use a Telit Wireless LE910C1-LA LTE/3G/2G radio modem. The design architecture consists of PC-Link communication channels to the control panel processor, and an optional radio module and Ethernet port for alarm communication to a monitoring station.

Technical specifications

Table 1: Environmental parameters

Environmental factor	Detail	
Temperature	-10 to + 55 °C	
Humidity	ty 0 to 95% RH (non-condensing)	
Environment	Indoor, home, office, industrial	

Table 2: Radio and product information

Item	Description	
Brand	DSC/ Johnson Controls/ TSP	
Module(s)	TL280LE-LAT	
	LE2080-LAT	
FCC ID	F5317TL280LER	
FCC Standards Applied	FCC Part 15B, Part 22, Part 24	
Radio Brand	Telit Wireless	
Radio Model	LE910C1-LA	
Cellular Operating Bands	See cellular operating bands and antenna gain	
Cellular Transmission Power	Typical values for max output level:	
	2 G(GSM):	
	LB: Class 4 (2 W, 33 dBm)	
	Class E2 (0.5 W, 27 dBm@EDGE)	
	HB: Class 1 (1W, 30 dBm)	
	Class E2 (0.4 V, 26d Bm@EDGE)	
	3G (WCDMA) : Class 3 (0.25 W, 24 dBm)	
	TD-SCDMA: Class 3 (0.4W, 26 dBm@EDGE) 4G (FDD and TDD): Class 3 (0.2 W, 23 dBm@1RB)	
Cellular Modulation Type	GSM/GPRS/EDGE: GMSK/8PSK	
	UMTS/HSPA: BPSK/QPSK LTE: QPSK/16QAM	
Communication Protocols	TCP/IP, UDP, GSM, GPRS, UMTS, LTE	
SAR Certificate	Not applicable as this is not a portable device and must be more than 20 cm from the human body	
Cellular Network / Operator Approval	Not Required	
Cellular Emission Designation	243KGXW, 244KG7W, 245KGXW, 4M13F9W,	
	4M24F9W, 17M8G7D, 5M26W7D, 5M25W7D, 8M92G7D, 4M90W7D, 5M18W7D	
Company name	Tyco Safety Products Canada Ltd.	
Company Address	3301 Langstaff Rd., Concord, ON, L4K4L2 Canada	
Manufacturer name	Johnson Controls Matamoros	
Manufacturing Location	Antonio Meucci #10002 Parque Industrial Las Ventanas.	
	Matamoros, Tamps. CP 87560 Mexico	
Country of Origin	Mexico	
TAC (LE910C1-LA)	35720968	
TAC Holder	Telit Communications SpA	

Table 3: Antenna parameters

Antenna detail	Parameter
Antenna Manufacturer	Cheerfar
Antenna Type	LTE Pentaband
Antenna Connector Type	RP-SMA

Cellular Operating Bands and Typical Antenna Gain

Table 4: Cellular operating bands and typical antenna gain

Product	Cell band	Operating frequency	Antenna gain (dBi)
TL280LE-LAT and LE2080-LAT	LTE B1	UL: 1920 - 1980	5.6
-Anatel, FCC, CNC Compliant		DL: 2110 - 2170	
NOM-019 / NOM-221 compliant	LTE B2	UL: 1850 – 1910	5.8
		DL: 1930 – 1990	
	LTE B3	UL:1710 - 1785	3.6
		DL: 1805 – 1880	
	LTE B4	UL: 1710 – 1755	4.5
		DL: 2110 – 2155	
	LTE B5	UL: 824 – 849 DL: 869 – 894	1.1
	LTE DZ		3.5
	LTE B7	UL: 2500 – 2570 DL: 2620 – 2690	3.5
	LTE DOG		-0.2
	LTE B28	UL: 703 – 748 DL: 758 – 803	-0.2
	WCDMA B1	UL: 1920 - 1980	5.6
	WCDIVIA BT	DL: 2110 - 2170	3.0
	WCDMA B2	UL: 1850 – 1910	5.8
	110011111111111111111111111111111111111	DL: 1930 – 1990	
	WCDMA B4	UL: 1710 – 1755	4.5
		DL: 2110 - 2155	
	WCDMA B5	UL: 824 - 849	1.1
		DL: 869 - 894	
	2G B2	UL: 1850 - 1910	5.8
		DL: 1930 – 1990	
	2G B3	UL: 1710 – 1785	3.6
		DL: 1805 – 1880	
	2G B5	UL: 824 - 849	1.1
		DL: 869 – 894	
	2G B8	UL: 880 - 915	2.6
		DL: 925 - 960	


Table 5: Emissions of harmonic/spurs frequencies (non-essential radiation according to UIT)

Frequency (MHz)	dBuV/m (at 10m)	
-	Class A	Class B

Block diagram

This block diagram illustrates the hardware functional layout. The functional block of the power supply includes several elements of switch mode and linear regulator circuits. Blocks in orange represent the main processor circuits, and blue represents communication links with the control panel. Functional blocks on the left with arrows represent connections with the control panel. Blocks with arrows on the right represent communication channels that may leave the cabinet.

Figure 1: Block diagram



Regulatory statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. This equipment complies with FCC and Industry standards RF radiation exposure limits set forth for an uncontrolled environment.

This equipment is to be installed and operated with a minimum distance of 20 centimeters between the radiator and your body. Under Industry Canada regulations, this radio transmitter only operates using an antenna of a type and maximum, or lesser, gain approved for the transmitter by Industry Canada.

To reduce potential radio interference to others, choose the antenna type and its gain so that the equivalent isotopically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

This device complies with Industry Canada license- exempt RSS standard. Operation is subject to the following two conditions: (1) this device must not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.